

## STEP 1: Wiring Connections

1. Plug the provided cable harness into the exposed socket on the side of the housing. Then screw the antenna into the port located on the opposite side from the cable socket.
2. Wire 12 to 18VDC or VAC power source to the RED and BLACK Power wires. If using DC, connect GND to the BLACK wire and V+ to the RED wire. If using AC, there is no polarity.
3. Wire the BLUE and WHITE wire to the input on the gate/door controller. This output is a Normally Open relay contact. Typically blue wire to circuit common and white wire will go into an open or free exit input.

## STEP 2: Programming and Operation

1. Follow the procedure on the backside of this guide to activate your SIM card with SpeedTalk Mobile. If you are using an alternate cell provider, ensure your plan is properly activated and configured. Insert the SIM card into the slot on the bottom of the housing (near the antenna port).
2. Apply power to the device and wait until the RED LED labeled "GSM" goes solid RED. If this LED never goes solid RED, or begins blinking, this indicates an issue with the cellular connection. Ensure the SIM is properly seated in the socket and try again. If the SIM is orientated correctly and the RED LED is still off, you may need to contact the cellular provider for back-end tech support.
3. Using another cell phone, text the messages as shown below. These messages are case sensitive.

**Command #1: Factory Default**

Send: *9999default*  
Receive: Warning Response  
Send: **YES (must be all caps)**  
Receive: Unit set to default

**Command #2: Adding Authorized User**

**NOTE:** Replace the number below with a phone that will be activating the Cell Opener365  
Send: *9999AN.12168655002*  
Receive: Confirming 12168655002 added

4. Using the cell phone that was added using "command #2" in step 3, call the phone number of the SIM card that is in the Cell Opener 365. The phone call will immediately be answered and hung up. If the phone number was properly added with the previous step, the relay will momentarily activate.

# Speedtalk Mobile GSM SIM Card Activation and QuickStart Guide

The CellOpener-365 includes a GSM Mobile SIM card provided by Speedtalk Mobile. Any other mobile carriers GSM Sim card that supports 4G and 4G LTE devices are compatible with the CellOpener-365.

If you choose to use Speedtalk Mobile as your provider, you can activate the enclosed SIM card using a credit card by going to [activate.speedtalkmobile.com](https://activate.speedtalkmobile.com)

1

Enter your SIM card number and email address. A verification code will be sent to your email that needs to be entered on this page as well.

2

Press the “To get a new phone number, Activate” button that is now showing.

To get a new phone number  
**Activate**

3

Enter the zip code that you would like the new phone number to have, or check the box for a random zip code

4

Select either the \$10 or \$25 service plan. The \$10 service plan will support up to 500 monthly communications, and the \$25 plan will support 1250 monthly communications. Select the best plan for your expected usage.

5

Enter your billing and payment information and the plan will be activated. An email will be sent with the cell openers new phone number.

**Activate Your Plan**

Please enter your SpeedTalk Mobile SIM card number below to activate:  
SPEEDTALK MOBILE SIM CARD NUMBER (NUMBERS ONLY)

Email:  
(Activation Confirmation will be emailed to this email address):

Verification Pin:  
Enter the verification PIN below that was sent to your email

< Back CONTINUE

## ZIP CODE for the new phone number:

44125

Have system pick a random USA zip code for me

Service Plan:

\$10 \$25 \$60 \$120

30 Days \$25.00 SELECT

Talk (MINUTES): 2¢/MIN

Text (SMS): 2¢/SMS

Data (5G 4G LTE) 2¢/MB

**\$25** 5G 4G LTE

Pay As You Go 30 DAYS

1250 MIN OR 1250 SMS OR 1250 MB

speedtalk mobile

NO CONTRACT NO CREDIT CHECK NO ACTIVATION FEE

< Back CONTINUE

### TIP:

To prevent service outages due to high usage, enable the “overages enrolment” setting. This will allow you to store additional minutes on your account that will only be used if the allotted monthly usage is completely consumed